



Ratchet Crimp Tool complete with die set for terminating COAX 75 ohm Micro BNC and DIN 1.0/2.3 suitable connectors to Canford group J and W broadcast cables. Die set has the following cavities:

0.95mm	(0.042")	A/F Square for centre contact
3.25mm	(0.128")	A/F Hex
4.52mm	(0.178")	A/F Hex
5.18mm	(0.204")	A/F Hex

Note that this tool may not be suitable for other brands of 75 ohm BNC, Micro BNC and DIN 1.0/2.3. Check die cavities required for your chosen connector.

Suitable connectors:

MICRO BNC-12G

- 48-5021 COAX CONNS 67-005-B66-AB MICRO BNC 12G UHD Male cable, group J
- 48-5031 COAX CONNS 67-005-B66-AB MICRO BNC 12G UHD Male cable, group J (pack of 100)
- 48-5025 COAX CONNS 67-005-B66-BH MICRO BNC 12G UHD Male cable, group W
- 48-5035 COAX CONNS 67-005-B66-BH MICRO BNC 12G UHD Male cable, group W (pack of 100)

DIN 1.0/2.3-3G

- 48-5001 COAX CONNS 52-005-B6-AB DIN 1.0/2.3 3G HD Male cable, group J
- 48-5011 COAX CONNS 52-005-B6-AB DIN 1.0/2.3 3G HD Male cable, group J (pack of 100)
- 48-5005 COAX CONNS 52-005-B6-BH DIN 1.0/2.3 3G HD Male cable, group W
- 48-5015 COAX CONNS 52-005-B6-BH DIN 1.0/2.3 3G HD Male cable, group W (pack of 100)